



| Titus Model | Unit Size | Rated Motor Current | | | Motor HP |
|--------------|-----------|------------------------|--------------|---------------|----------|
| | | (Single-phase, 60hz)** | | | |
| | | 120 Volt | 208 or 240 V | 277 or 480* V | |
| TFS(F) | B | 2.3 | 0.9 | 0.8 | 1/6 |
| | C | 4.0 | 1.8 | 1.4 | 1/4 |
| | D | 8.5 | 3.6 | 3.0 | 1/3 |
| | E | 8.6 | 4.2 | 4.5 | 3/4 |
| TFS(F) w/ECM | B | 3 | n/a | 1.6 | 1/3 |
| | C | 4.6 | n/a | 2.1 | 1/3 |
| | D | 5.6 | n/a | 2.8 | 1/2 |
| | E | 9.7 | n/a | 4.9 | 3/4 |
| TQS | 2 | 4.0 | 1.8 | 1.3 | 1/6 |
| | 3 | 7.0 | 3.0 | 2.4 | 1/4 |
| | 4 | 9.8 | 4.1 | 2.9 | 1/3 |
| | 5 | 10.0 | 4.3 | 3.3 | 1/3 |
| | 6 | 13.4 | 7.2 | 5.4 | 3/4 |
| | 7 | n/a | 9.0 | 6.5 | 1 |
| TQS w/ECM | 4 | 7.7 | n/a | 4.1 | 1/2 ECM |
| | 6 | 12.8 | n/a | 6.9 | 1 ECM |
| TQP | 2 | 3.6 | 1.5 | 1.3 | 1/6 |
| | 3 | 5.3 | 2.6 | 2.2 | 1/4 |
| | 4 | 7.8 | 3.2 | 2.9 | 1/3 |
| | 5 | 9.2 | 3.3 | 3.2 | 1/3 |
| | 6 | 12.3 | 6.3 | 5.4 | 3/4 |
| TQP w/ECM | 4 | 6.2 | n/a | 3.1 | 1/2 ECM |
| | 6 | 11.4 | n/a | 6.5 | 1 ECM |
| FLS | 2 | 3.9 | 1.6 | 1.2 | 1/6 |
| | 3 | 5.8 | 2.4 | 1.8 | 1/4 |
| | 4 | 8.2 | 3.4 | 2.5 | (2) 1/6 |
| FLS w/ECM | 3 | 4.2 | n/a | 2.3 | 1/3 ECM |
| | 4 | 8.5 | n/a | 5 | 1/3 ECM |
| FLP | 2 | 4.3 | 1.8 | 1.3 | 1/6 |
| | 4 | 5.4 | 2.3 | 1.7 | 1/4 |
| LHK | 3 | 5.8 | 2.5 | 1.8 | 1/4 |
| | 4 | 6.4 | 3.0 | 2.5 | 1/3 |
| LHK w/ECM | 3 | n/a | n/a | 2.4 | 1/3 ECM |
| | 4 | 3.9 | n/a | 2.3 | 1/3 ECM |
| PFC | 14 | 7.0 | 3.1 | 3.2 | 1/3 |

| | | | | | |
|------------------|----|------|-----|-----|---------|
| | 16 | 11.4 | 5.2 | 5.1 | 3/4 |
| PFC w/ECM | 14 | 6.1 | n/a | 2.6 | 1/2 ECM |
| | 16 | 11.2 | n/a | 6.2 | 1 ECM |

*480 Volt models use 277 volt motors.

**Three-phase models use single-phase motors.