



Redefine your comfort zone.™

| Titus Model         | Unit Size        | Rated Motor Current<br>(Single-phase, 60hz)** |              |               | Motor HP   |
|---------------------|------------------|---|--------------|---------------|------------|
|                     |                  | 120 Volt                                      | 208 or 240 V | 277 or 480* V |            |
|                     |                  |   |              |               |            |
| <b>TFS(F)</b>       | A                | 1.25  | 0.6          | 0.54          | 1/10       |
|                     | B                | 2.3   | 0.9          | 0.8           | 1/6        |
|                     | C                | 4.0   | 1.8          | 1.4           | 1/4        |
|                     | D                | 8.5   | 3.6          | 3.0           | 1/3        |
|                     | E                | 8.6   | 4.2          | 4.5           | 3/4        |
|                     | G                | n/a   | 13.2         | 9.9           | (2) 3/4    |
| <b>TFS(F) w/ECM</b> | B                | 5.0   | 3.3          | 2.6           | 1/3 ECM    |
|                     | C                | 5.0   | 3.3          | 2.6           | 1/3 ECM    |
|                     | D                | 7.7   | 5.0          | 4.1           | 1/2 ECM    |
|                     | E                | 9.6   | 7.9          | 5.5           | 3/4 ECM    |
|                     | G                | 25.6  | 21.0         | 13.8          | (2) 1 ECM  |
| <b>TQS</b>          | 2                | 4.0   | 1.8          | 1.3           | 1/6        |
|                     | 3                | 7.0   | 3.0          | 2.4           | 1/4        |
|                     | 4                | 9.8   | 4.1          | 2.9           | 1/3        |
|                     | 5                | 10.0  | 4.3          | 3.3           | 1/3        |
|                     | 6                | 13.4  | 7.2          | 5.4           | 3/4        |
|                     | 7                | n/a   | 9.0          | 6.5           | 1          |
|                     | <b>TQS w/ECM</b> | 4   | 7.7          | 5.0           | 4.1        |
| 6                   |                  | 12.8  | 10.5         | 6.9           | 1 ECM      |
| <b>TQP</b>          | 2                | 3.6   | 1.5          | 1.3           | 1/6        |
|                     | 3                | 5.3   | 2.6          | 2.2           | 1/4        |
|                     | 4                | 7.8   | 3.2          | 2.9           | 1/3        |
|                     | 5                | 9.2   | 3.3          | 3.2           | 1/3        |
|                     | 6                | 12.3  | 6.3          | 5.4           | 3/4        |
| <b>TQP w/ECM</b>    | 3 & 4            | 7.7   | 5.0          | 4.1           | 1/2 ECM    |
|                     | 5 & 6            | 12.8  | 10.5         | 6.9           | 1 ECM      |
| <b>FLS</b>          | 2                | 3.9   | 1.6          | 1.2           | 1/6        |
|                     | 3                | 5.8   | 2.4          | 1.8           | 1/4        |
|                     | 4                | 8.2   | 3.4          | 2.5           | (2) 1/6    |
| <b>FLS w/ECM</b>    | 3                | 5.0   | 3.3          | 2.6           | 1/3 ECM    |
|                     | 4                | 10.0  | 6.6          | 5.2           | (2)1/3 ECM |
| <b>FLP</b>          | 2                | 4.3   | 1.8          | 1.3           | 1/6        |
|                     | 4                | 5.4   | 2.3          | 1.7           | 1/4        |
| <b>LHK</b>          | 3                | 5.8   | 2.5          | 1.8           | 1/4        |
|                     | 4                | 6.4   | 3.0          | 2.5           | 1/3        |
| <b>LHK w/ECM</b>    | 3                | 5.0   | 3.3          | 2.6           | 1/3 ECM    |
|                     | 4                | 5.0   | 3.3          | 2.6           | 1/3 ECM    |
| <b>PFC</b>          | 10               | 3.4   | 1.7          | 1.7           | 1/4        |
|                     | 14               | 7.0   | 3.1          | 3.2           | 1/3        |
|                     | 16               | 11.4  | 5.2          | 5.1           | 3/4        |
| <b>PFC w/ECM</b>    | 10               | 5.0   | 3.3          | 2.6           | 1/3 ECM    |
|                     | 14               | 7.7   | 5.0          | 4.1           | 1/2 ECM    |
|                     | 16               | 12.8  | 10.5         | 6.9           | 1 ECM      |

\*480 Volt models use 277 volt motors.

\*\*Three-phase models use single-phase motors.